

Features

- Maximum power of 80 W
- Interchangeable lenses
- Remote control
- Color temperature 5600 K (± 200 K)
- Possibility to mount GOBO filters
- Power supply via NP-F or included power supply
- Glow control in the range of 5 - 100%
- Color reproduction at CRI ≥ 97
- Compact size

Specification

Model	Quadralite SVL-800S
Power	80 W
Dimensions of the lamp	29 x 12 x 10 cm
Color temperature	5600 K (± 200 K)
CRI	≥ 97
TLCI	≥ 98
Photometry	8600 lux / 1 m
Cooling fan	Yes
Dimmable	Stepless dimming 5 - 100%
Mounting	5/8" stem and 1/4" threaded mounting point
Adjustable beam angle	15 - 40°
LED technology	COB
LED Brand	CREE
Voltage	110 - 240 V
Frequency	50 - 60 Hz
Average lifetime	50000 Hours
Power Supply	AC/DC power supply, 2x NP-F with adapter or dedicated type battery (14.8 V)
Weight	1269 g



- Power knob (on/off)
- Brightness knob (brightness adjustment)
- Battery release
- Focusing ring
- Shoe mount
- DC power input
- LCD Display

User Manual

SVL-800S

LED light





Focusing Lens L-60



Product Name	Lens
Model Code	L-60
Brand	Quadralite
Lens Type	For optical snoot use
Compatible Mounting	Canon EF
Focus Mode	Manual
Material	Metal + Optical Glass
Fixed Focal Length	60 mm
Aperture Value	F2.8
Focus Range	0.3 m - ∞
Size	68 x 58 mm
Weight	280 g

Maintenance and Warranty

- If the device's casing is damaged, for instance as a result of a fall, you are advised to immediately stop using the device and send it back to Quadralite servicing point, where the device will be examined and possibly fixed.
- The manufacturer gives 2 years warranty for the device.
- Any modifications to the device are unacceptable and result in the immediate loss of warranty.
- All mechanical damages and damages resulting from improper use of the device are not covered by the warranty.
- Device modifications made by the user or unauthorized technical service are unacceptable and result in the loss of all warranty claims.
- The device cannot be immersed in water, while its surface should not be cleaned with detergents. Only surface cleaning is allowed.
- Before cleaning the device turn it off and disconnect from the power source.
- The manufacturer is not liable for any damages resulting from improper operation of the equipment, therefore you should only use the device in compliance with this user manual.

CONTACT US :

www.quadralite.pl
info@quadralite.pl

Thanks for Purchasing

CE RoHS