

Quadralite Navigator X Plus P

Navigator X Plus transmitter allows you to wirelessly control studio strobes and speedlights made by Quadralite. You can use manual mode to precisely adjust flash power output from the distance up to 100 m. However automatic flash metering mode (TTL) is also available together with high-speed sync as well (up to 1/8000s)¹. Front and second curtain sync is also possible².

Navigator X Plus combines almost all features of previously released Navigator X2 with a small and compact housing of the first generation Navigator X transmitters. However there are few major upgrades. First and the most significant is integrated Bluetooth used to connect with Quadralite Photo App enabling comfortable adjusting flash power and modeling light directly on your smartphone screen (Android and iOS devices are supported). Another novelty in relation to its predecessor is the appearance of five buttons on the top left part of the housing, which open the direct access to the control of five groups of strobes. The flash output adjustment scale has also changed. It is much more accurate and now you can adjust flash power in 0.1 f-stop increments³. Device menu hides another new feature which is scan function. You can use it to search for communication channels without radio interference that can influence connection between lights and the transmitter itself. Control dial and all important buttons are located on the left side of the housing, which means that you don't have to take the right hand off the camera grip to make any changes in the light set-up.

Top part of the housing is fitted with additional shoe which can be used to connect additional radio trigger on the top of Navigator X Plus⁴. Front panel is equipped with red light used to assist autofocus of the camera⁵. This feature is especially useful in low light scenarios on-location or inside studio as well. Transmitter can be easily attached to the camera thanks to integrated quick action hot shoe clamp. There is also 3.5mm Jack sync port and USB-C socket as well. Device is powered by two AA batteries.

Navigator X Plus features:

- Wireless controller for all Quadralite X wireless system devices
- Available in six variants: Canon, Nikon, Sony, Fujifilm, MFT (Olympus, Panasonic) and Pentax camera¹
- Compatible with automatic TTL flash light metering system
- 2.4 GHz wireless transmission ensures stable work on longer distances both in studio and on location (up to 100m)
- 32 communication channels and 5 groups for fast configuration and control over many lights
- AF assist helps to adjust focus distance in poor light conditions
- equipped with five direct access buttons (A/B/C/D/E) to group settings
- built-in Bluetooth allows to connect with Quadralite Photo App installed on phone and tablet
- HSS (High Speed Sync) up to 1/8000
- integrated quick action hot shoe clamp
- ergonomically arranged keys and control knob
- fitted with additional hot shoe on top
- 2-way Jack 3.5mm sync port available
- firmware update is possible through built-in USB-C



¹ It is required to match transmitter variant to the given camera brand to ensure full compatibility.

² Depending on the version. For more details, refer to the transmitter's instruction manual.

³ Not all flashes support this feature. For more details, refer to the flash instruction manual.

⁴ The upper hot-shoe is not designed to support speedlights of any type and size.

⁵ Autofocus assist light does not work with all cameras. For more details, refer to the transmitter's instruction manual.

Specification

Model	Quadralite Navigator X Plus P
Product type	TTL&HSS-capable radio trigger
Compatible with	Pentax
Flash Modes	TTL/M/Multi/OFF
High Speed Sync	up to 1/8000 s
Range	100 m
Frequency	2.4 GHz
Mode	Master
Channels	32
Groups	5
Power source	2 x AA
Sync socket	2.5mm Jack
Firmware upgrade	Yes (via USB-C Port)
Ready indicator	Visual
Display	Dot-matrix hi-contrast LCD
Operating temperature range	+10°C do +50°C
Length x Height x Width	70 x 72 x 80 mm
Weight	90 g (battery not included)

**EAN:** 5901698718312**Warranty:** 2 years**Box:** 108x105x70mm**Kit includes:**

- Navigator X Plus P transmitter
- Instruction manual